

# QSG RUT901

[Main Page](#) > [RUT Routers](#) > [RUT901](#) > **QSG RUT901**

## Safety information

Before starting operating the device, please review recommendations and precautions to minimize the possibility of accidents. Safety precautions presented are supplementary and subject to the local safety regulations. When various operations are executed on the device, the user must fully follow the safety instructions and recommendations provided with the device.



### Contents

- [1 Safety information](#)
- [2 Safety information](#)
  - [2.1 General](#)
  - [2.2 RF exposure](#)
  - [2.3 Operating conditions](#)
  - [2.4 Faulty and damaged products](#)
  - [2.5 Electrical safety](#)
  - [2.6 Product handling](#)
- [3 Front view](#)
- [4 Back view](#)
- [5 Connectors](#)
- [6 Hardware installation](#)
- [7 Configure your computer LAN \(Windows\)](#)
- [8 Configure your computer Wi-Fi \(Windows\)](#)
- [9 Login to device](#)
- [10 SIM card recommendations](#)



## Safety information

Before starting operating the device, please review recommendations and precautions to minimize the possibility of accidents. Safety precautions presented are supplementary and subject to the local safety regulations. When various operations are executed on the device, the user must fully follow the safety instructions and recommendations provided with the device.

---

### General

| Radio specifications                |  |
|-------------------------------------|--|
| RF technologies                     | 2G, 3G, 4G, Wi-Fi  |
| Max RF power                        | 33 dBm@GSM, 24 dBm@WCDMA, 23 dBm@LTE, 20 dBm@Wi-Fi                                     |
| Bundled accessories specifications* |  |
| Power adapter                       | Input: 0.45A@100-240 VAC, Output: 9 VDC, 1A, 4-pin plug                                |
| Mobile antenna                      | 698~960/1710~2690 MHz, 50 Ω, VSWR<3, gain** 4 dBi, omnidirectional, SMA male connector |

Wi-Fi antenna 2400~2500 MHz, 50 Ω, VSWR<2.5, gain\*\* 5 dBi, omnidirectional, RP-SMA male connector

\* Order code dependant.

\*\* Higher gain antenna can be connected to compensate for cable attenuation when a cable is used. The user is responsible for the compliance with the legal regulations.

RUT901 router must be used in compliance with any and all applicable national and international laws and with any special restrictions regulating the utilization of the communication module in prescribed applications and environments.

## CE Declaration of Conformity

|                       |  |
|-----------------------|--|
| <b>[BG] Bulgarian</b> | С настоящето, TELTONIKA NETWORKS декларира, че RUT901 е в съответствие със съществените изисквания и другите приложими разпоредби на Директива 2014/53/EU                            |
| <b>[HR] Croatian</b>  | Ovim TELTONIKA NETWORKS izjavljuje da je ovaj RUT901 u skladu s bitnim zahtjevima i ostalim relevantnim odredbama Direktive 2014/53/EU   |
| <b>[CZ] Czech</b>     | TELTONIKA NETWORKS tímto prohlašuje, že RUT901 splňuje základní požadavky a všechna příslušná ustanovení Směrnice 2014/53/EU   |
| <b>[DK] Danish</b>    | Undertegnede TELTONIKA NETWORKS erklærer herved, at følgende udstyr RUT901 overholder de væsentlige krav og øvrige relevante krav i direktiv 2014/53/EU                              |
| <b>[NL] Dutch</b>     | Hierbij verklaart TELTONIKA NETWORKS dat het toestel I RUT901 in overeenstemming is met de essentiële eisen en de andere relevante bepalingen van richtlijn 2014/53/EU               |
| <b>[EE] Estonian</b>  | Käesolevaga kinnitab TELTONIKA NETWORKS seadme RUT901 vastavust direktiivi 2014/53/EU põhinõuetele ja nimetatud direktiivist tulenevatele teistele asjakohastele sätetele            |
| <b>[FI] Finish</b>    | TELTONIKA NETWORKS vakuuttaa täten että RUT901 tyypinen laite on direktiivin 2014/53/EU oleellisten vaatimusten ja sitä koskevien direktiivin muiden ehtojen mukainen                |
| <b>[FR] French</b>    | TELTONIKA NETWORKS déclare que cette RUT901 est conforme aux exigences essentielles et aux autres dispositions pertinentes de la directive 2014/53/EU                                |
| <b>[DE] German</b>    | Hiermit erklärt TELTONIKA NETWORKS, dass dieser RUT901 den grundlegenden Anforderungen und anderen relevanten Bestimmungen der Richtlinie 2014/53/EU entspricht                      |
| <b>[GR] Greek</b>     | ΜΕ ΤΗΝ ΠΑΡΟΥΣΑ Ο ΚΑΤΑΣΚΕΥΑΣΤΗΣ ΤΗΛΤΟΝΙΚΑ ΝΕΤΟΥΡΚΣ ΔΗΛΩΝΕΙ ΟΤΙ Η ΡUT901 ΣΥΜΜΟΡΦΩΝΕΤΑΙ ΠΡΟΣ ΤΙΣ ΟΥΣΙΩΔΕΙΣ ΑΠΑΙΤΗΣΕΙΣ ΚΑΙ ΤΙΣ ΛΟΙΠΕΣ ΣΧΕΤΙΚΕΣ ΔΙΑΤΑΞΕΙΣ ΤΗΣ ΟΔΗΓΙΑΣ 2014/53/EU          |
| <b>[HU] Hungarian</b> | A TELTONIKA NETWORKS ezzennel kijelenti, hogy a RUT901 típusú berendezés teljesíti az alapvető követelményeket és más 2014/53/EU irányelvben meghatározott vonatkozó rendelkezéseket |
| <b>[IE] Irish</b>     | Leis seo, dearbhaíonn TELTONIKA NETWORKS go gcomhlíonann an RUT901 seo bunriachtanais agus forálacha ábhartha eile Threoir 2014/53/EU  |
| <b>[IT] Italian</b>   | Con la presente, TELTONIKA NETWORKS dichiara che questo RUT901 è conforme ai requisiti essenziali e ad altre disposizioni pertinenti della Direttiva 2014/53/EU                      |

|                        |   |
|------------------------|---|
| <b>[LV] Latvian</b>    | Ar šo TELTONIKA NETWORKS deklarē, ka RUT901 atbilst Direktīvas 2014/53/EU būtiskajām prasībām un citiem ar to saistītajiem noteikumiem  |
| <b>[LT] Lithuanian</b> | Šiuo dokumentu UAB TELTONIKA NETWORKS deklaruoja, kad šis RUT901 atitinka esminius reikalavimus ir kitas 2014/53/EU Direktyvos nuostatas                                      |
| <b>[MT] Maltese</b>    | Hawnhekk, TELTONIKA NETWORKS tiddikjara li dan l-RUT901 huwa konformi mar-rekwiżiti essenzjali u dispozizzjonijiet rilevanti oħra tad Direttiva 2014/53/EU                    |
| <b>[NO] Norwegian</b>  | TELTONIKA NETWORKS Erklærer herved at RUT901 er i samsvar med de grunnleggende krav og øvrige relevante krav i direktiv 2014/53/EU  |
| <b>[PL] Polish</b>     | Niniejszym TELTONIKA NETWORKS deklaruje że RUT901 jest zgodny z zasadniczymi wymaganiami i innymi właściwymi postanowieniami Dyrektywy 2014/53/EU                             |
| <b>[PT] Portuguese</b> | Eu, TELTONIKA NETWORKS declaro que o RUT901 cumpre os requisitos essenciais e outras provisões relevantes da Directiva 2014/53/EU   |
| <b>[RO] Romanian</b>   | Prin prezenta, TELTONIKA NETWORKS declară că aparatul RUT901 este în conformitate cu cerințele esențiale și cu alte prevederi pertinente ale Directivei 2014/53/EU            |
| <b>[SK] Slovak</b>     | Spoločnosť TELTONIKA NETWORKS týmto vyhlasuje, že smerovač RUT901 je v súlade so základnými požiadavkami a ďalšími príslušnými ustanoveniami smernice 2014/53/EU              |
| <b>[SI] Slovenian</b>  | TELTONIKA NETWORKS izjavlja, da je ta RUT901 v skladu z bistvenimi zahtevami in drugimi relevantnimi določili direktive 2014/53/EU  |
| <b>[ES] Spanish</b>    | Por la presente, TELTONIKA NETWORKS declara que este RUT901 cumple con los requisitos esenciales y otras exigencias relevantes de la Directiva 2014/53/EU                     |
| <b>[SE] Swedish</b>    | Härmed intygar TELTONIKA NETWORKS att denna RUT901 är i överensstämmelse med de väsentliga egenskapskrav och övriga relevanta bestämmelser som framgår av direktiv 2014/53/EU |





### **Simplified EU and UK Declaration of Conformity**

Hereby, TELTONIKA NETWORKS declares that this RUT901 is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU and with Radio Equipment Regulations 2017. The full text of the EU and UK Declaration of Conformity is available at the following internet address: [wiki.teltonika-networks.com/view/Certificates](http://wiki.teltonika-networks.com/view/Certificates).

### **NCC Warning Statement**

- Without permission granted by the NCC, any company, enterprise, or user is not allowed to change frequency, enhance transmitting power or alter original characteristic as well as performance to a approved low power radio-frequency devices. The low power radio-frequency devices shall not influence aircraft security and interfere legal communications; If found, the user shall cease operating immediately until no interference is achieved. The said legal communications means radio communications is operated in compliance with the Telecommunications Management Act. The low power radio-frequency devices must be susceptible with the interference from legal communications or ISM radio wave radiated devices.
- Use with caution to minimize electromagnetic impacts.
- Standard MPE: 0.45 mW/cm<sup>2</sup>, actual value measured on product: 0.09 mW/cm<sup>2</sup>. It is advised to keep the antenna at least 20 cm away from human body when using the device.

Detailed compliance information is available at the following internet address: [wiki.teltonika-networks.com/view/Certificates](http://wiki.teltonika-networks.com/view/Certificates).

-  This sign means that it is necessary to read the User's Manual before you start using the device.
-  This sign on the package means that all used electronic and electric equipment should not be mixed with general household waste.
-  Hereby, TELTONIKA NETWORKS declares that this RUT901 is in compliance with the essential requirements and other relevant provisions of Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:  
[https://wiki.teltonika-networks.com/view/RUT901\\_CE/RED](https://wiki.teltonika-networks.com/view/RUT901_CE/RED)
-  Hereby, TELTONIKA NETWORKS declares that the radio equipment type RUT901 is in compliance with Radio Equipment Regulations 2017. The full text of the UK declaration of conformity is available at the following internet address:  
[https://wiki.teltonika-networks.com/view/RUT901\\_UKCA](https://wiki.teltonika-networks.com/view/RUT901_UKCA)

## RF exposure

---

This device meets the official requirements for exposure to radio waves. This device is designed and manufactured not to exceed the emission limits for exposure to radio frequency (RF) energy set by authorized agencies. The device must be used with a minimum separation of 20 cm from a person's body to ensure compliance with RF exposure guidelines. Failure to observe these instructions could result in your RF exposure exceeding the applicable limits.

External antennas used with RUT901 must be installed to provide a distance of at least 20 cm from any people and must not be co-located or operated in conjunction with any other antenna or transmitter.

Any external antenna gain must meet RF exposure and maximum radiated output power limits of the applicable rule section.

### Maximum transmission power

|       |        |
|-------|--------|
| GSM   | 33 dBm |
| WCDMA | 24 dBm |
| LTE   | 23 dBm |
| Wi-Fi | 20 dBm |

## Operating conditions

---

- Operating temperature: -40° to +75° Celsius
- Humidity should be in the range of 10% to 90% (non-condensing). Only use the device in dry environments.
- Out of direct sunlight
- Away from heat source, corrosive substances, salts, and flammable gases

**Attention:** operation outside the permissible range can considerably shorten the service life of the device.

## Faulty and damaged products

---

- Do not attempt to disassemble the device or its accessories.
- Only qualified personnel must service or repair the device or its accessories.
- If your device or its accessories have been submerged in water punctured or subjected to a severe fall, do not use until they have been checked at an authorized service center.

## Electrical safety

---

- Only use approved accessories.
- Do not connect with incompatible products or accessories.
- It is recommended to ground devices with grounding terminals before connecting them to power. Failure to ground appropriately might result in a shock hazard. The cross-sectional area of the protective grounding conductor should be at least 1mm<sup>2</sup>.

## Product handling

---

- You alone are responsible for how you use your device and any consequences related to its use.
- Use of your device is subject to safety measures designed to protect users and their environment.
- Always treat your device and its accessories with care and keep it in a clean and dust-free place.
- Do not expose your device or its accessories to open flames, lit tobacco products, liquid, moisture, or high humidity.
- Do not drop, throw or try to bend your device or its accessories.
- Do not use harsh chemicals, cleaning solvents, or aerosols to clean the device or its accessories.
- Do not paint your device or its accessories.
- Do not attempt to disassemble your device (exemptions for devices that require disassembly for SIM insertion) or its accessories: it does not contain any user-serviceable parts. For safety reasons, the equipment should be opened only by qualified personnel.
- Make sure to use ESD personal protective equipment while the equipment is serviced.
- Do not use your device in an enclosed environment where heat dissipation is poor.
- Prolonged use in such space may cause excessive heat and raise ambient temperature, which will lead to the automatic shutdown of your device or the disconnection of the mobile network connection for your safety. To use your device again after such a shutdown, cool it in a well-ventilated place before turning it on.
- Please check all national laws and local regulations for the disposal of electronic products.
- Do not operate the device where ventilation is restricted.
- Do not use or install this product near water to avoid fire or shock hazards.
- Avoid exposing the equipment to rain or damp areas.
- Arrange power and Ethernet cables so that they are not likely to be stepped on or have items

placed on them.

- Ensure that the voltage and the rated current of the power source match the device's requirements. Do not connect the device to an inappropriate power source.
- During a thunderstorm, no operations should be carried out on the device and cables.
- The unit must be powered off where blasting is in progress and explosive atmospheres are present or near medical life support equipment.
- Do not leave your device and its accessories within reach of small children or allow them to play with it. They could hurt themselves or others and could accidentally damage the device. Your device contains small parts with sharp edges that may cause an injury choking hazard.
- Like any wireless device, this device operates using radio signals, which cannot guarantee connection in all conditions. Therefore, you must never rely solely on any wireless device for emergency communications or otherwise use the device in situations where the interruption of data connectivity could lead to death, personal injury, property damage, data, or other loss.
- The device may become warm during regular use.

## Front view



## Back view



## Connectors


### POWER SOCKET PINOUT




## Hardware installation



## Configure your computer LAN (Windows)

1. Ensure the   
Network  
connection is  
Enabled. Go to  
Start — Control  
Panel —  
Network and  
Internet —  
Network and  
Sharing  
Center. Click  
on the **Change  
adapter  
settings** in the  
left panel, then  
right-click on  
Network  
Adapter, and  
select Enable.

---


2. Check if IP   
and DNS are  
obtained  
automatically.  
Right-click on  
Wireless  
Network  
Adapter and  
select  
Properties.  
Then select  
**Internet  
Protocol  
Version 4** and  
click  
Properties.  
3. If not  
selected, check  
to **obtain an  
IP address**  
and **obtain  
DNS server  
address  
automatically**.  
Click OK.

---

## Configure your computer Wi-Fi (Windows)

1. Ensure the   
Wireless  
network  
connection is  
Enabled. Go to  
Start — Control  
Panel —  
Network and  
Internet —  
Network and  
Sharing  
Center. Click  
on the **Change  
adapter  
settings** in the  
left panel, then  
right-click on  
Wireless  
Network  
Adapter, and  
select Enable.

---

2. Check if IP   
and DNS are  
obtained  
automatically.  
Right-click on  
Wireless  
Network  
Adapter and  
select  
Properties.  
Then select  
**Internet  
Protocol  
Version 4** and  
click  
Properties.  
3. If not  
selected, check  
to **obtain an  
IP address**  
and **obtain  
DNS server  
address  
automatically**.  
Click OK.

---

4. Connect to a   
wireless  
network by  
right-clicking  
on Wireless  
Network  
Adapter and  
selecting  
Connect.


---



5. Choose the   
wireless  
network  
RUT901 \*\*\*\*  
from the list  
and click  
Connect. Enter  
the Wi-Fi  
password  
located on the  
device's label.

---

## Login to device

1. To enter the   
router's Web  
interface  
(WebUI), type  
<http://192.168.1.1>  
into the URL field  
of your Internet  
browser.

2. When  
prompted for  
authentication  
enter the  
username admin  
and enter the  
password located  
on the device  
information  
label/engraving.

---

3. After logging in, you must set a new password for security reasons. You will not be able to interact with the router's WebUI until the default password is changed. The new password must consist of a minimum of **8 characters**. Requirements: one uppercase letter, one lowercase letter, and one digit.

4. Next, the Configuration Wizard will start to help you set up some of the router's main operational parameters.

5. Finally, let's verify the Mobile signal strength. Go to the **Status — Network** page and pay attention to the **Signal Strength** indication.

To achieve the best signal conditions and maximize cellular performance, try adjusting the antennas or changing the location of your device. You can find information on signal strength recommendations [here](#).

## SIM card recommendations

- Before installing the SIM cards, please apply a thin layer of dielectric grease to the SIM card contacts for devices used in environments with **high-vibration levels**. This will help avoid SIM cards losing touch with the SIM slot and prevent unexpected failures.
- Industrial Grade SIM cards are recommended for devices requiring a long lifespan used in environments with **extreme temperatures, corrosive** or **extra humid climates**, or hard-to-

reach locations.