

		PSTN	Redcare	GSM
E00	Bad command ¹	•	•	•
E01	Bad parameter	•		•
E10	Generic connection failure			
E11	Busy Tone			•
E12	No Carrier	•		•
E13	Protocol Error	²		•
E14	Kiss-off Timeout			•
E18	No Dial Tone			•
E20	Generic modem not ready			
E21	Modem not ready - Communications channel unavailable			
E22	Modem not ready			
E30	A SIM PIN is required and was not provided			•
E31	The SIM is blocked and a PUK is required			•
E32	The SIM is waiting phone-to-SIM card password			•
E33	The SIM PIN provided was incorrect			•
E34	Unknown PIN Error			•
E40	Line fault	•	•	•
E41	Dual path line fault		³	
E42	Signal Too Weak			•
E43	No SIM Present			•
E44	SIM Changed			•
E45	SIM is Roaming			•
E50	Modem Could not Start			•
E51	Modem Not Responding			•
E90	Operation timeout	•		•
E130-E138	Protocol Error	•		

¹ Bad Command error is returned by the modem if it receives an unrecognized command.

² Protocol errors for PSTN are E130-E138. See bottom of this table.

³ Error defined for Redcare, but not currently used.