

DS-PR501-HWE

Tri-X wireless receiver, compatible with AX Hybrid Pro control panel, used to expand wireless capability of the control panel. HIKVISION Tri-X detectors can be added to AX Hybrid Pro panel via this wireless receiver.

- 868MHz wireless receiver
- Wireless transmission distance up to 1600m
- Supports 32 wireless detectors, 8 wireless indoor sounders and 4 wireless outdoor sounders

▪ Specification

Software features	
Compatibility list	DS-PK1-E-WE DS-PS1-I-WE DS-PS1-E-WE DS-PKF1-WE DS-PDP15P-EG2-WE DS-PDD12P-EG2-WE DS-PDMCS-EG2-WE DS-PDMC-EG2-WE DS-PDWL-E-WE DS-PDEB1-EG2-WE、DS-PDEB2-EG2-WE DS-PDEB1-EG2-WE(B) DS-PDEB2-EG2-WE(B) DS-PDP15P-EG2-WE(B) DS-PDP18-HM-WE DS-PDMC-EG2-WE(B) DS-PDMCK-EG2-WE(B) DS-PDBG8-EG2-WE DS-PDTPH-E-WE DS-PDCL12-EG2-WE DS-PDC10DM-EG2-WE DS-PDC10AM-EG2-WE DS-PDTP15AM-LM-WE DS-PDQP15AM-LM-WE DS-PDSMK-E-WE DS-PDHT-E-WE DS-PDCO-E-WE
Hardware features	
Bus	1 input for control panel connection and 1 output for bus extender
Electrical characteristics	
Typical voltage	12 VDC
Power supply	9-16VDC, up to 3A, provided by bus
Power consumption	Quiescent Current 90 mA @12VDC Maximum Current 150 mA @12VDC
Wireless transmission	
RF frequency	868.0-868.6 MHz
Wireless technology	Tri-X Wireless Technology
RF distance 改为 : Transmission Range(Free Space)	1600m (Open area)

▪ Available Model

DS-PR501-HWE

DS-PM643-WE(RU)

See Far, Go Further



www.hikvision.com
support@hikvision.com

