

DHI-ICS1-W2(868) Smart Plug



The Smart Plug is a highly intuitive power switch. It can be remotely controlled through the mobile app, scheduled to turn on and off, and set to activate automatically when alarms are triggered or the system is armed or disarmed.

Scene

Suitable for scenes where remote control, electrical safety and energy efficiency are prioritized such as houses, stores and office buildings.

| Technical Specification | | |
|-------------------------|--|--|
| Port | | |
| Relay Output | 1 port, NO/NC (100–240 VAC, max 16 A) | |
| Wireless | | |
| Indicator Light | 1 indicator light, displays multiple status Flash green: paring Solid green: the circuit is closed Light off: the circuit is open | |
| Remote Update | Supports cloud update | |
| Button | 1 button, perform multiple operations (open/close the circuit, restore to the factory settings and pair) | |
| Signal Strength | Supports detecting signal strength. | |
| Frequency Range | 868-868.6 MHz | |
| Communication Distance | In an open environment: 1,600 m (5249.34 ft) | |
| MAX Power | 865-868.6 MHz@16.15 dBm | |
| Communication Mechanism | Two-way communication. | |
| Encryption | AES-128 | |
| Frequency Hopping | Yes | |

- Two-way RF communication.
- Displays the status with an LED indicator.
- Supports cloud update and auto recovery after an update fails.
- Offers protection against overcurrent, overvoltage, and overheating.
- Measure the voltage, current and temperature.
- Generates power consumption statistics and it can be reset to clear the statistics.
- Output control mode can be selected between bistable and pulse modes.

General

| Indoor: –10 °C to +55 °C (+14 °F to +131 °F) | |
|--|--|
| 10%–90%(RH), non-condensing | |
| –10 °C to +55 °C (+14 °F to +131 °F) | |
| 10%–90%(RH), non-condensing | |
| 100–240 VAC, 50/60 Hz | |
| 52 mm × 52 mm × 82 mm (2.05" × 2.05" × 8.32") (L × W × H) | |
| With power strip/2 Pin | |
| 83 g (0.18 lb) | |
| 0.3 W | |
| CE | |
| PC | |
| | |
| Yes | |
| Current; voltage; temperature | |
| | |
| Protection range: 0 A–16 A Measurement Accuracy: level 1.0 and above. | |
| Protection range: 0 V –250 V Measurement Accuracy: level 1.0 and above. | |
| Protection range: 0°C –55 °C Measurement Accuracy: ±2% or ±2 °C | |
| | |
| Alarm for overcurrent, overvoltage, and overheating | |
| | |

Smart Plug | DHI-ICS1-W2(868)

| Ordering Information | | | |
|----------------------|------------------|-------------|--|
| Туре | Model | Description | |
| Smart Plug | DHI-ICS1-W2(868) | Smart Plug | |

Installation



Application



Dimensions (mm[inch])







Rev 002.000 © 2024 Dahua. All rights reserved. Design and specifications are subject to change without notice. The images, specifications and information mentioned in the document are only for reference, and might differ from the actual product.