

## **Floor Mount Door Holder**





Model: YD-606L

#### **Basic Instruction**

Dual Voltage Selectable (12VDC or 24VDC) Emergency Release Button/Test Button Wall Mounting Direction

Low Current Consumption Reliable Fail-Safe Mechanism **Durable and Silence Operation** 

#### **Specifications**

Size: 90Lx90Wx128H(mm)

Voltage: 12/24VDC(Adjustment)

Current Draw: 12V/240mA 24V/120mA

• Optional: Manual door release button

Surface Temp: ≤+20°C

Operating Temp: 0~+55<sup>°</sup>C(14-131F)


• Weight: 1.8kg


- Holding Force: 180kg(350Lbs)
- Suitable for: All Kinds of Single(Double) Smokeproof Doors
- Suitable Humidity: 0~95%
- Finishes for Shell: High Temperature Paint Environmental

**Protection Zinc** 

• Finishes for Armature: Chromium

#### **Dimension**







### Installation

# 12/24V Adjustable

#### Remarks:

- 1. The default setting is 24VDC.
- 2. If user want to connect with 12VDC, operating as below:
- (1) Pull those two jumpers out. It is showed 4 pins here.
- (2) To set up 12VDC, insert one jumper on the position of 1 and 2, second jumper on the position of 3 and 4.





We create security www.yli.cn